

## REPLACEMENT PARTS LIST

Ref. Symbol	Jackson Stock No.	Name and Description		
R27	27-229	RESISTOR:	WIRE WOUND	3500 ohm 10w
R28	27-232	RESISTOR:	COMPOSITION	33000 ohm 1/2w
R29	27-228	RESISTOR:	COMPOSITION	100000 ohm 1/2w
R30	27-306	RESISTOR:	COMPOSITION	220000 ohm 1/2w
R31	27-265	RESISTOR:	WIRE WOUND	5000 ohm 5w 5%
R32	4-66	POTENTIOMETER:	WIRE WOUND	50000 ohm
R33	27-459	RESISTOR:	WIRE WOUND	15000 ohm 5w
R34	27-411	RESISTOR:	COMPOSITION	47 ohm 1/2w
R35	4-103	POTENTIOMETER:	CARBON	50000 ohm
L1		COIL:	SWEEP BAND "A"	
L2		COIL:	SWEEP BAND "B"	
L3		COIL:	SWEEP BAND "C"	
L4		COIL:	114 MC	
L5		COIL:	MARKER BAND "A"	
L6		COIL:	MARKER BAND "B"	
L7		COIL:	MARKER BAND "C"	
L8	15-65	CHOKE:	10 MICRO HENRY	
L9		CHOKE:		
L10		CHOKE:		
L11	15-54	CHOKE:	2.5 MIL HENRY	
L12	15-65	CHOKE:	10 MICRO HENRY	
L13		CHOKE:		
L14		CHOKE:		
L15	14-46	CHOKE:	50 MA.	
L16	15-54	CHOKE:	2.5 MIL HENRY	
L17	15-87	COIL:	VIDEO PEAKING	
L18		COIL:	114 MC OUTPUT	
M1	37-1	DRIVE UNIT:	P.M.	
T1	14-62	TRANSFORMER:	POWER	
T2	14-24	TRANSFORMER:	MODULATION	
T3	14-57	TRANSFORMER:	SWEEP CONTROL	
S1	8-94	SWITCH:	ROTARY, 2 CIR, 3 POS.	
S2	8-93	SWITCH:	ROTARY, 3 CIR, 3 POS.	
S3	8-95	SWITCH:	ROTARY, 1 CIR, 8 POS.	
S4	8-105	SWITCH:	ROTARY, 3 CIR, 3 POS.	
S5	8-98	SWITCH:	ROTARY, 2 CIR, 4 POS.	
S6	8-45	SWITCH:	TOGGLE, S.P.S.T.	
S7	8-45	SWITCH:	TOGGLE, S.P.S.T.	
S8	8-45	SWITCH:	TOGGLE, S.P.S.T.	
S9	8-85C	SWITCH:	ROTARY, 1 CIR, 5 POS.	
J1	5-47A	JACK:	MIDGET	
J2	5-71	HOLDER:	CRYSTAL	
J3	5-43	CONNECTOR:	CHASSIS	
J4	5-43	CONNECTOR:	CHASSIS	
J5	5-43	CONNECTOR:	CHASSIS	
J6	5-43	CONNECTOR:	CHASSIS	
X1	34-5	RECTIFIER:	CRYSTAL DIODE	